

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

### High Voltage ESS

Last Update: 2024/9/11

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver	Installation
					Activation	Force Charge		
Ingeteam Power Technology	ISS 1Play 3TL / 6TL	Powercube X1/X2/H1/H2 Powercube X1/X2/H1/H2-V2 Powercube-M1C Force H1/H2 Force-H3	CAN	On/off-grid	Yes	Yes	ABH1002AA ABH1003_Q(disp)	Wall mounting
	ISS 1Play 3TL M / 6TL M		CAN	On/off-grid	Yes	Yes	ABH1007_A ABH1003_Q(disp)	Wall mounting
Solis	RHI-3P-HVES-5G series S6-EH3P(5-10)K-H-EU S6-EH1P(3.8-11.4)K-H-US S6-EH3P(29.9-50)K-H		CAN	On/off-grid	Yes	Yes		Wall mounting
SMA <sup>b</sup> Solar Technology AG	SBS 3.7-10 - SBS6.0-10		CAN	On/off-grid	Yes	Yes	04.04.03.R	Wall mounting
KOSTAL <sup>c</sup> Industrie Elektrik GmbH	PLENTICORE plus PLENTICORE plus G2 PLENTICORE BI xx/26 PLENTICORE BI xx/26 G2 PLENTICORE G3		RS485	On/off-grid	Yes	Yes		Wall mounting
KACO	NH3 Series		CAN	On/off-grid	Yes	Yes		Wall mounting
Sungrow	SH5.0/6.0/8.0/10.0RT		CAN	On/off-grid	Yes	Yes	SAPPHIRE-H_V11_V01_A	Wall mounting
Delios s.r.l.	DLX HV series		CAN	On/off-grid	Yes	Yes	V3.00	Wall mounting
Goodwe	EH/BH series ET/BT 5-10KW		CAN	On/off-grid	Yes	Yes	V14	Wall mounting
EATON	xStorage Home 3P Series		CAN	On/off-grid	Yes	Yes	V3.00	Wall mounting
SolarMax	ES-T Series		CAN	On/off-grid	Yes	Yes	V3.00	Wall mounting
Deye(Sunsynk)	SUN-5~25K-SG01HP3-EU/AU SUN-29.9~50K-SG01HP3-EU/AU <sup>a</sup>		CAN	On/off-grid	Yes	Yes	2001-X018	Wall mounting
Sol-Ark	30K-3P-208V-N 60K-3P-480V-N		CAN	On/off-grid	Yes	Yes	1066	Wall mounting
Lux Power	Hybrid HB series		CAN	On/off-grid	Yes	Yes		Wall mounting
Redback	RB-HVS(ST10000)(1) RB-HVS-AC(SB7200)(2)		Modbus RTU	On/off-grid	Yes	Yes	V2.6(1) V2.9(2)	Cabinet
Sofar	HYD 10000/15000/20000 TL-3PH		CAN	On/off-grid	Yes	Yes	FW: D0110036 DSP: V010027	Wall mounting
Sunways	STH-4-12KTL-HT series STH-3-8KTL-HS series		CAN	On/off-grid	Yes	Yes	ARM: V0054	Wall mounting
	STR-4-12KTL-HT series STR-3-8KTL-HS series							
eCACTUS	WH-SPA-3.68H(1) WH-SPA-5.0H(1) WH-SHC series(2) WH-THA series(2)		Modbus RTU	On/off-grid	Yes	Yes	21426-004R(1) 21426-005R(1) 511-00007-03(2)	Wall mounting
Senergy	SE 3K~6KHB-HV SE 5K~30KHB-D3		CAN	On/off-grid	Yes	Yes	V010000	Wall mounting
Salicru S.A.	EQX2 3001-8002-HSX series EQX2 4002-12002-HT series	CAN	On/off-grid	Yes	Yes	V1 . 28 . 45 . 04 . 00	Wall mounting	
HYPONTECH	HHS series(1) HBS series(1) HHT series(2) HBT series(2)	CAN	On/off-grid	Yes	Yes	Ver.23(1) Ver.29(2)	Wall mounting	

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.  
For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

### High Voltage ESS

Last Update: 2024/9/11

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver	Installation
					Activation	Force Charge		
AISWEI(Solplanet)	ASW06H/08H/10H/12H/15H-T1(1) ASW05kH/06kH/08kH/10kH/12kH-T2(2) ASW08kH/10kH/12kH-T3(2)	Powercube X1/X2/H1/H2 Powercube X1/X2/H1/H2-V2 Powercube-M1C Force H1/H2 Force H1/H2-V2 Force-H3	CAN	On/off-grid	Yes	Yes	DSP:1.04.00(1) ARM:V610-60005-02(1) V610-05001-00(2)	Wall mounting
SOLINTEG	MHT-4~20K Series MHT-25~50K Series MHS-3~8K Series MRT-4~20K Series MRT-25~50K Series MRS-3~8K Series		CAN	On/off-grid	Yes	Yes	ARM: V01(08)	Wall mounting
ETEK	ETH-3~8KTL-HS Series ETH-4~20KTL-HT Series ETH-25~50KTL-HT Series		CAN	On/off-grid	Yes	Yes	ARM: V01(08)	Wall mounting
MEGAREVO	R6~15KH3 Series		CAN	On/off-grid	Yes	Yes	ARM:V1.02.13 DSP:V1.03.14	Wall mounting
	R5~12KH1NA Series						ARM:V1.01.41 DSP:V1.02.20	
Hoymiles	HYT-HV Series		CAN	On/off-grid	Yes	Yes	Power - V00.04.07 Safety - V00.04.06 System - V00.02.18	Wall mounting
	HAT-HV Series							
KOYOE	KY-EST06KH-KY-EST20KH		CAN	On/off-grid	Yes	Yes	320701	Wall mounting
INVT	XD5/6/8/10/12KTR		CAN	On/off-grid	Yes	Yes	208-208-0-319	Wall mounting
Afore	AF3~9.6K-DH Series AF3~30K-TH Series AF3~12K-THP Series AF3~17K-THA Series AF3~6K-THC Series AF3~15K-THM Series AF3~7K-THMA Series AF3~30K-TH-0 Series AF3~12K-THP-0 Series AF3~15K-THM-0 Series AF3~7K-THMA-0 Series		CAN	On/off-grid	Yes	Yes	1.01	Wall mounting
Solavita	SWH3000 ~ 6000H-S1 SWH005 ~ 15KH-T1	CAN	On/off-grid	Yes	Yes	V0.8.10/V2.0.5	Wall mounting	
AUXSOL	ASG-3.6~6SL-ZH Series ASG-5~12TL-ZH Series	CAN	On/off-grid	Yes	Yes	A2507	Wall mounting	
YARD FORCE	PG3700/4600/5000-SH	CAN	On/off-grid	Yes	Yes	V0011	Wall mounting	
Dream Maker	PCS-3-4~20kW-25(40)A-1 PCS-1-3~8kW-30A-1 PCS-3-25~50kW-100A-1	CAN	On/off-grid	Yes	Yes	ARM: V01(08)	Wall mounting	
SAJ	H2-3K~6K-S2 H2-5K~10K-T2	CAN	On/off-grid	Yes	Yes	V1.018	Wall mounting	
SINENG	SN3~6HSU series	CAN	On/off-grid	Yes	Yes	00003000(ARM)	Wall mounting	
CE+T	Sierra 25 (380Vdc) <sup>d</sup>	CAN	On/off-grid	Yes	No	V16.12.0	Cabinet	
YI ENERGY	HI-3P5K-H-Y1 HI-3P6K-H-Y1 HI-3P8K-H-Y1 HI-3P10K-H-Y1 HI-3P12K-H-Y1	CAN	On/off-grid	Yes	Yes	DSPM:00.00.02.00; DSPS:00.00.01.01; ARM:00.01.01.08;	Wall mounting	
LEDIT	FVDx series	CAN	On/off-grid	Yes	Yes	V3.00	Wall mounting	
Sermatec	SMT-10K/30K/50K-TL-TH	CAN	On-grid	Yes	Yes		Wall mounting	

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.  
For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

### High Voltage ESS

Last Update: 2024/9/11

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver	Installation
					Activation	Force Charge		
Imeon Energy	3/3.7/4.6/5HV		CAN	On/off-grid	Yes	Yes	V1.10	Wall mounting
Tsun	TSOL-H/A-3.0~6.0K-H		CAN	On/off-grid	Yes	Yes	DSP:V1.0, ARM:V1.14	Wall mounting
GMDE	TB5200TD		CAN	On-grid	Yes	Yes	1.0.3	Wall mounting
Voltronic	Infinisolar TX-PA 30K	Powercube H1/H2 Powercube H1/H2-V2 Powercube M1/M2/M3	Modbus RTU	On/off-grid	Yes	Yes	2008.27.12	Cabinet
Blue Mountain Energy	BME-20 BME-30		Modbus RTU	On/off-grid	Yes	Yes	21-01-27 DSP:2101.2212 MCU:2011.1712	Cabinet
ATESS	HPS30/50/100/120/150		CAN	On/off-grid	Yes	Yes	HPS30K_150K_HV3_ SV9.1.39	Cabinet
MEGAREVO	MPS0030~0500 Series		CAN	On/off-grid	Yes	Yes	V302B400D014	Cabinet
	MEGA0030~0500TS Series MEGA0500/MEGA0630						V102B500D014	
Growocol	GW-MPS0030~0500 Series		CAN	On/off-grid	Yes	Yes	V302B400D014	Cabinet
Efacec	Battery Inverter		Customized with additional EMS	On/off-grid				Cabinet
Ferroamp	EnergyHub							
Pramac	PBI Series							
Sungrow	SC series							
Sinexcel	PWS/PWG series							
Kehua	BCS series							

<sup>a</sup> When compatible with Deye hybrid inverter mentioned in the list above, make sure the Battery Controller firmware is as below or higher:  
(1) Force-H1/H2: V1.7; (2) Force-H1/H2-V2: V1.1; (3) Powercube-X/H: V5.7; Powercube-X/H-V2: V1.2.

<sup>b</sup> Only Force-H1-V2 and Force-H2-V2 are compatible with SMA Sunny Boy Storage inverters mentioned in the list above.

<sup>c</sup> Only Force-H1-V2 and Force-H2-V2, Force-H3 are compatible with Kostal PLENTICORE series inverter mentioned in the list above.

<sup>d</sup> Only Powercube X/H and Powercube X/H V2 series are compatible with CE+T inverter mentioned in the list above.

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.  
For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

Last Update: 2024/9/11

### 48V ESS

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
					Activation	Force Charge	
Victron Energy	Multiplus 48V (via Venus OS)	US2000 US2000V2 US3000 US2000C US3000C US5000 US5000-B UP5000 UF5000 Phantom-S Force-L1/L2 Pelio-L	CAN	On/off-grid <sup>a</sup>	Yes	Yes	422/V2.15
	Quattro 48V (via Venus OS)		CAN	On/off-grid <sup>a</sup>	Yes	Yes	422/V2.15
SMA Solar Technology AG	SI 4.4-M		CAN	On/off-grid <sup>d</sup>	No	Yes	
	SI 6.0-H						
	SI 8.0-H						
	SI 6048US						
Schneider-Electric	Conext XW Pro series		CAN	On/off-grid	Yes	Yes	Gateway: V1.06 XW+ Pro: V1.04 (UL) / V1.05 (IEC)
Goodwe	GW-BP		CAN	On-grid	Yes	Yes	
	SBP GW-ES <sup>h</sup>		CAN	On-grid	Yes	Yes	
	EM		CAN	On-grid	Yes	Yes	
Imeon Energy	IMEON 3.6		CAN	On/off-grid	Yes	Yes	V1.7.6.5
	IMEON 9.12		CAN	On/off-grid	Yes	Yes	V1.7.6.5
Studer Innotec	Xtender 48V serie		CAN	On/off-grid	Yes	Yes	R652
	VarioString serie		CAN	On/off-grid	Yes	Yes	R652
	VarioTrack 48V serie		CAN	On/off-grid	Yes	Yes	R652
Selectronic	SPMC 480		CAN	On/off-grid	No	Yes	
	SPMC 481		CAN	On/off-grid	No	Yes	
	SPMC 482		CAN	On/off-grid	No	Yes	
Voltronic	Infinisolar series 48V		RS485(9600)	On/off-grid	Yes	Yes	V1.00
	Axpert series 48V <sup>b</sup>		RS485(9600)	On/off-grid	Yes	Yes	V2.61
Sofar	ME3000SP	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2	
	HYD series	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2	
CHINT POWER	ECH3K ~ 6K-SML-EU ECA3K ~ 6K-SNL-EU	CAN	On/off-grid	Yes	Yes	LCD: 29.08 DSP: 05.95	
AP systems	ELS-5K	CAN	On-grid	Yes	Yes	Hardware version Rev1.2.4 Software version Rev1.2.X	
Sermatec	SMT-5K-TL-LV	RS485(9600)/CAN	On/off-grid	Yes	Yes		
Zucchetti Centro Sistemi	Azzurro 3000SP	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2	
	Azzurro HYD3000/6000-ES	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2	
	RHI/RAI series	CAN	On/off-grid	PV only	Yes	90009	

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.

For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

Last Update: 2024/9/11

### 48V ESS

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
					Activation	Force Charge	
Solis	S5-EA1P3K-L S6-EA1P(3.6-6)K-L S6-EO1P(4-5)K-48 S5-EH1P(3-6)K-L S6-EH1P(3-6)K-L-EU	US2000 US2000V2 US3000 US2000C US3000C US5000 US5000-B UP5000 UF5000 Phantom-S Force-L1/L2 Pelio-L	CAN	On/off-grid	PV only	Yes	
Redback	SH5000		RS485(115200)	On-grid	PV only	No	
Deye (Sunsynk)	SUN-SG01LP1 series		CAN	On/off-grid	Yes	Yes	V1586
	SUN-SG03LP1 series		CAN	On/off-grid	Yes	Yes	V1586
	SUN-SG04LP1 series		CAN	On/off-grid	Yes	Yes	
	SUN-SG04LP3 series		CAN	On/off-grid	Yes	Yes	
Alpha & Outback Energy	SPCIII-5000-48		RS485 (9600)	Off-grid	Yes	Yes	91.24
	SPCIII-7200-48						45.06
	SPCIIIS-5000-48						71.1
Lux Power	LXP 3-6K Hybrid		CAN	On/off-grid	Yes	Yes	AA1.0
	ACS series	AA1.0					
	SNA series	AA1.0					
	LXP-LB-EU Series	EA1.0 (for 8K/10K model) fA1.0 (for 12K model)					
	LXP-LB-US Series						
Sungrow	SH5K	CAN	On-grid	Yes	Yes	V13	
Morningstar	TriStar MPPT in 48V	N/A	On/off-grid	PV only	No	v32b	
	TriStar MPPT 600V in 48V	N/A	On/off-grid	PV only	No	v32b	
	TriStar PWM TS-45 in 48V	N/A	On/off-grid	PV only	No	v32b	
	GS-MPPT-60M/80M/100M-200V <sup>f</sup>	CAN	On/off-grid	PV only	No	v2.0	
Delios s.r.l.	DLS/C series	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27	
	DLS AC series	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27	
Ingeteam Power Technology	ISS 1Play TL M series	CAN	On/off-grid	Yes	Yes	ABH1007_D	
MLT	Oasis 448	US2000 US2000V2	N/A	Off-grid	No	Yes	V2.19
	Oasis 648						V2.19
Steca	Solarix PLI 5000-48	US3000 US2000C US3000C US5000	N/A	Off-grid	Manual	No	
SAI	Sunfree series	US2000 US2000V2 US3000 US2000C US3000C US5000	RS485(9600)	On/off-grid	Yes	Yes	V2.031/V1.037

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.

For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)



# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

Last Update: 2024/9/11

### 48V ESS

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
					Activation	Force Charge	
SolarMax	H1 series	US5000-B UP5000 UF5000 Phantom-S Force-L1/L2 Pelio-L	CAN	On/off-grid	Yes	Yes	V2.094/V1.318
	ES series		CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
	AC series		CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
Growatt	SPH 3000 - 6000		CAN	On/off-grid	No	Yes	RA1.0
	SPF 2000 - 5000 HVM-48/ LVM-48P <sup>C</sup>		RS485(9600)	On/off-grid	No	Yes	GW500.08/502.05/503.03/507.03
	SPF 5000 ES / SPF 6000 ES PLUS		CAN	On/off-grid	Yes	Yes	Main CPU 067.02 / Slave CPU 068.02
	SPF 12000T DVM-US		CAN	On/off-grid	Yes	Yes	
	M2000H/3000H/5000H - 48 <sup>C</sup>		RS485(9600)	On/off-grid	No	Yes	SK001.11/012.06/013.03/035.00
Sol-Ark	Sol-Ark-5K/8K-48-ST, Sol-Ark-5K-120V, Sol-Ark-8K-120/230V, Sol-Ark-8K-230-1P, Sol-Ark-12K-P, Sol-Ark-12K-3P-380V, Limitless 15K-LV		CAN	On/off-grid	Yes	Yes	V1430
AXIOMA energy	ISPWM 5000		US2000 US2000V2 US3000 US2000C US3000C US5000 US5000-B UP5000 UF5000 Phantom-S Force-L1/L2 Pelio-L	N/A	On/off-grid	No	No
	ISMPT BF 3000 - 5000	N/A		On/off-grid	No	No	
	ISGRID (BF) 3000 - 5000	N/A		On/off-grid	No	No	
Phocos	Any-grid PSW-H-5kW-230/48V	RS485(9600)		On/off-grid	Yes	Yes	V1.00
Western CO.	LEONARDO PRO 3000/48 Li (via Western LK3)	CAN		On/off-grid	Yes	Yes	V1.1
EFFEKTA	AX-M1 4000/5000-48 (via Com Box)	RS485(9600)		On/off-grid	Yes	Yes	54.40/74.40
	AX-K1 4000/5000-48 (via Com Box)	RS485(9600)		On/off-grid	Yes	Yes	14.40/34.40
	AX-M2 4000/5000-48	RS485(9600)		On/off-grid	Yes	Yes	51.00/72.01
Kehua	SPH5000-BL	CAN		On-grid	Yes	Yes	V1.00.013
Noark	Ex9N-DH-3~8KS-AU series Ex9N-DH-5~12KT-AU series	CAN		On/off-grid	Yes	Yes	V1139
INVT	BD series	CAN	On/off-grid	Yes	Yes	V1.06	
	Kinergier Pro: CK-II 2.0S-3.0S (1) CK-II 2.0M-3.0M(2), CK4.0S-8.0S(3)				No		LCD:V1.13 DSP:V1.24(1) LCD:V1.14 DSP:V1.11(2) LCD:V1.28

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.

For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

Last Update: 2024/9/11

### 48V ESS

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver	
					Activation	Force Charge		
TBB	Kinergier Pro-II: CK-II 3.0M-8.0S		CAN	On/off-grid	Yes	Yes	LCD:V2.00 DSP:V2.00	
	RiiO: 2KVA - 6KVA(1) RiiO II: 3KVA - 8KVA(2) RiiO Sun: 2KVA - 6KVA(3) RiiO Sun II: 3KVA - 8KVA(4)				Yes		LCD:V1.11 DSP:V2.06 (1) LCD:V1.04 DSP:V1.03(2) LCD:V1.11 DSP:V2.06 MPPT:V1.10(3) LCD:V1.04 DSP:V1.03(4)	
	Apollo Matrix: 3.0M-5.0S				Yes		LCD:V1.15 DSP:V1.24 MPPT:V1.10	
	Apollo Maxx: 2.0M-5.0S				Yes		LCD:V1.11 DSP:V1.11 MPPT:V1.10	
	Tyrann Series: 10.0S-15.0S				Yes		LCD:V1.0 DSP:V1.0	
EPEVER	UP3000-HM5041(RTU)		RS485(115200)		Yes	Yes	SV1.73	
	UP3000-HM8041(RTU)						SV1.82	
	UP3000-HM5042(RTU)						SV1.83	
	UP5000-HM8042(RTU)						SV1.84	
Afore	AF1~3.6K-SL-1 Series AF3~6K-SL Series AF4~6K-SLP Series AF1~3.6K-ASL-1 Series AF3~6K-ASL Series AF1~6K-SL-0 Series AF1~6K-ASL-0 Series		CAN	On/off-grid	Yes	Yes	1.01	
MUST	PV1800 VHM 3KW - 5.5KW	US2000 US2000V2 US3000 US2000C US3000C US5000 US5000-B UP5000 UF5000 Phantom-S Force-L1/L2 Pelio-L	CAN	On/off-grid	No	Yes	1.17.06	
Moixa	Smart Battery V4 3000		CAN	On-grid	Yes	Yes	V2.2.1	
	GridShare Hub		CAN	On-grid	Yes	Yes	V2.2.1	
MEGAREVO	RKL1 Series		CAN	On/off-grid	Yes	Yes	ARM: 1.00.28 DSP: 1.01.23	
	R5K/6K/7K/8KLNA		CAN	On/off-grid	Yes	Yes	ARM:1.03.12 DSP:1.04.11	
AISWEI	ASW3000/3680/4000/5000H-S		CAN	On/off-grid	Yes	Yes	master v610-02001-00	
	ASW3000/3680/4000/5000/6000H-S2						DSP:V610-02003-01 Safetv:V610-10008-03	
SOROTEC	REVO II - 48V Series			CAN	On/off-grid	Yes	Yes	Inverter:1.5.4 Control board: 64
	REVO E PLUS - 48V Series				Off-grid			
	REVO VM II - 48V Series							
	REVO VM PLUS - 48V Series							
FSP Power Solution GmbH	PowerManager series 4-15kW Offgrid PMI III / Zero		RS485(9600)	On/off-grid	Yes	Yes	V1.00 V2.61	

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.

For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)

# Compatibility List of Pylontech ESS and Inverters

## Ver.2.33.xlsx

Last Update: 2024/9/11

### 48V ESS

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
					Activation	Force Charge	
Senergy	SE 4K6/5K/6KHB-60/120	US2000 US2000V2 US3000 US2000C US3000C US5000 US5000-B UP5000 UF5000 Phantom-S Force-L1/L2 Pelio-L	RS485(9600) <sup>e</sup>	On/off-grid	PV only	Yes	0.6.0
	No				Yes		
Livolttek	Hyper series		CAN	On/off-grid	Yes	Yes	1.78
	Retro series				Yes	Yes	
	GF1-3K/5K48S1		Off-grid	Yes	Yes	ARM V0.59 DSP V0.13	
	BV1-3K/5K48S1			Yes	Yes		
Hoymiles	HYS-LV Series		CAN	On/off-grid	Yes	Yes	Power - V01.04.19 and above Safety - V01.02.13 and above System - V00.02.18
	HAS-LV Series						
CE+T	Sierra 25 (48Vdc)		CAN	On/off-grid	Yes	No	V16.4.0
EAST	EAHI-3000 ~ 6000-SL		RS485	On/off-grid	Yes	Yes	master V1001, dsp V1004
LEDIT	FVDi series	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27	
Growocol	MKS IV 5.6KW -B MKS IV 6KW TWIN MAX II-8000	RS485(9600)	On/off-grid	Yes	Yes		
OPTI-Solar	SP5000 Brilliant series	RS485(9600)	On/off-grid	Yes	Yes	V1.00/00.32	
	SP5000 Regal/Handy Plus	RS485(9600)	On/off-grid	Yes	Yes	V1.00/00.32	
	SP4000/10000 Premium	RS485(9600)	On/off-grid	Yes	Yes	V1.00/00.32	

<sup>a</sup> When compatible with Victron Multi/Quattro in off-grid application via Venus-device, it is required to have a Victron MPPT or other compatible PV inverter with Victron to avoid the system getting shut down.

<sup>b</sup> When compatible with Voltronic Axpert series, only VM III and King two types are available for RS485 communication, for the rest types of Axpert only available for manual settings. When using VM III and King, only launch firmware 02.61 or higher can work with Force L1/L2.

<sup>c</sup> When compatible with Growatt SPF/M series corresponding type, according to inverter logic, the depth of discharge(DoD) of battery shall be set to 80% or lower. Otherwise may lead to system shut down and need of manually recharge battery.

<sup>d</sup> When compatible with SMA SI4.4-M / SI6.0-H / SI8.0-H, it's required to follow the min. configuration table from SMA for a guaranteed configuration. The Force L1/L2 is not compatible with SMA SI series.

<sup>e</sup> When compatible with Senergy inverter, max. configure 1 string of battery system, donot support multiple strings' connection.

<sup>f</sup> When compatible with GS-MPPT-60M/80M/100M-200V, it requires optional ReadyBMS accessory.

<sup>g</sup> When compatible with P721730001, please make sure the discharge cut off voltage is higher than 47V.

<sup>h</sup> Not Compatible with Pelio-L and UF5000.

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.

For any inquiries, please contact: [service@pylontech.com.cn](mailto:service@pylontech.com.cn)